





























# 5G NR/4G LTE CPE

# Mobile broadband product portfolio











	5G NR					Cat. 18	Cat. 12	Cat. 6	Cat. 4
Outdoor Router	 <b>NR7501</b> 5G NR	 <b>NR7303</b> 5G NR	 <b>NR7302</b> 5G NR	 <b>NR7301</b> 5G NR	 <b>NR7103</b> 5G NR	 <b>LTE7490-M904</b> 4G LTE-A Pro	 <b>LTE7480-M804</b> 4G LTE-A		
	 <b>NR7102</b> 5G NR								
Indoor Router	 <b>NR5306</b> 5G NR	 <b>NR5304</b> 5G NR	 <b>NR5303</b> 5G NR	 <b>NR5103</b> 5G NR	 <b>NR5103E</b> 5G NR	 <b>LTE5398-M904</b> 4G LTE-A Pro	 <b>LTE5388-M804</b> 4G LTE-A	 <b>LTE3301-PLUS</b> 4G LTE-A	 <b>LTE3202-M437</b> 4G LTE
	 <b>NR5103EV2</b> 5G NR								

# Key features

Category	Cat.	Model	Key features
Outdoor CPE	5G NR	NR7501 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 7.5 Gbps/2.9 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz &amp; mmWave aggregation</li> <li>Built-in mmWave AiP (Antenna in Package) with Max. EIRP 50 dBm</li> <li>Built-in Sub-6 GHz 4x4 MIMO, high-gain antennas of up to 12 dBi per element</li> <li>Standard 802.3bt 5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-143 speed test) and web GUI</li> <li>IP68 hardened enclosure with industrial grade components</li> </ul>
		NR7303 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>Standard 802.3af/at 2.5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7302 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 4.0 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 3CC with 200 MHz channel bandwidth</li> <li>Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>Standard 802.3af/at 2.5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7301 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 3.4 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 120 MHz channel bandwidth</li> <li>Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>Standard 802.3af/at 2.5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7103 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>Standard 802.3af/at 2.5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>IP68 hardened enclosure with industrial grade components</li> </ul>
		NR7102 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 5 Gbps/650 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>Standard 802.3af/at 2.5G PoE</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>IP68 hardened enclosure with industrial grade components</li> </ul>
		Cat. 18	LTE7490-M904 
Cat. 12	LTE7480-M804 	<ul style="list-style-type: none"> <li>3GPP Release 12 Cat. 12, up to 600/150 Mbps* (DL/UL)</li> <li>Built-in 4x4 MIMO, directional high-gain antennas of up to 7 dBi per element</li> <li>Multiple APNs with VLAN mapping</li> <li>Remote management via TR-069 (with TR-143 speed test), HTTP/web GUI</li> <li>IP68 hardened enclosure with industrial-grade components</li> </ul>	

\* All models support Zykel Air app (iOS and Android)

\*\* The maximum data rate is a theoretical value. The actual data rate depends on the operator.

Category	Cat.	Model	Key features
Indoor CPE	5G NR	NR5306 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 4.0 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 3CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> </ul>
		NR5304 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 3.4 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 120 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> </ul>
		NR5303 	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 5.4 Gbps/250 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 4CA with 300 MHz channel bandwidth</li> <li>WiFi 6E (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> </ul>
		NR5103 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 4x4+4x4 for superior performance and coverage</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
		NR5103E 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
		NR5103EV2 	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
		Cat. 18	LTE5398-M904 
Cat. 12	LTE5388-M804 	<ul style="list-style-type: none"> <li>3GPP Release 12 Cat. 12, up to 600/150 Mbps* (DL/UL)</li> <li>AC2050 dual-band WiFi AP</li> <li>Dual-WAN Failover (mobile &amp; Ethernet WAN)</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>Supports VoIP/VoLTE (optional feature)</li> </ul>	
Cat. 6	LTE3301-PLUS 	<ul style="list-style-type: none"> <li>3GPP Release 10 Cat. 6, up to 300/50 Mbps* (DL/UL)</li> <li>AC1200 dual-band concurrent links</li> <li>Supports seamless switching between 4G and 3G</li> <li>Dual-WAN Failover (mobile &amp; Ethernet WAN)</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> </ul>	
Cat. 4	LTE3202-M437 	<ul style="list-style-type: none"> <li>3GPP Release 9 Cat. 4, up to 150/50 Mbps* (DL/UL)</li> <li>N300 WiFi with multiple simultaneous SSIDs</li> <li>Seamless switching between 4G and 3G</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> </ul>	

# Frequency band comparison

## Outdoor CPE

Model	5G NR						Cat. 18	Cat. 12	
	NR7501	NR7303	NR7302	NR7301	NR7103	NR7102	LTE7490-M904	LTE7480-M804	
<b>Product name</b>	5G NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router	4G LTE-A Pro Outdoor Router	4G LTE-A Outdoor Router	
<b>Ingress Protection Rating</b>	IP68	IP67	IP67	IP67	IP68	IP68	IP68	IP68	
<b>5G NR</b>	<b>FDD</b>	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	-	-	
	<b>TDD</b>	n38, n40, n41, n77, n78, n257, n258, n260, n261	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78, n75	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78	-	-
<b>4G LTE</b>	<b>FDD</b>	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28	
	<b>TDD</b>	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41	
<b>DL CA</b>		5G NR: 2xCA (FR1+FR2) 5G NR: 3xCA (FR1) 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 3xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: EN-DC 4G LTE: 7xCA	DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band DL 4xCA: intra-band and inter-band DL 5xCA: intra-band and inter-band within 4 bands	DL 2xCA: intra-band and inter-band DL 3xCA: intra-band and inter-band
	<b>UL CA</b>	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	2xCA: intra-band contiguous	2xCA: intra-band contiguous
<b>MIMO</b>		5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78/n257/n258/ n260/n261 4G LTE DL: 4x4 MIMO on B1/B3/B7/ B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/ B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/ B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n20/ n28/n38/n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B40/ B41/B42/B43	DL MIMO: B1/3/7	DL MIMO: B1/3/7
	<b>Modulation (DL/UL)</b>	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/64-QAM	256-QAM/64-QAM
<b>WiFi</b>	<b>802.11n 2x2</b>	Yes*	Yes*	Yes*	Yes*	Yes*	Yes*	Yes*	
	<b>802.11ac 2x2</b>	-	-	-	-	-	-	-	
	<b>802.11ac 4x4</b>	-	-	-	-	-	-	-	
	<b>802.11ax 2x2</b>	-	-	-	-	-	-	-	
	<b>Number of users</b>	-	-	-	-	-	-	-	-
<b>Ethernet</b>	<b>GbE LAN</b>	x1 (5GbE PoE)	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)	x1 (1GbE PoE)	
	<b>GbE WAN</b>	-	-	-	-	-	-	-	
<b>Phone</b>	<b>VoIP</b>	-	-	-	-	-	-	-	
	<b>Vo3G/VoLTE</b>	-	-	-	-	-	-	-	
<b>SIM slot</b>	<b>Micro/Mini SIM slot</b>	Micro SIM	Micro SIM	Micro SIM	Micro SIM	Micro SIM	Micro SIM	Micro SIM	
<b>Power</b>	<b>DC input</b>	PoE 48 V	PoE 48 V	PoE 48 V	PoE 48 V	PoE 48 V	PoE 48 V	PoE 48 V	

\* WiFi AP is used for management purpose only.

# Frequency band comparison

## Indoor CPE

Model		5G NR					
		NR5306	NR5304	NR5303	NR5103	NR5103E	NR5103EV2
<b>Product name</b>		5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router
<b>5G NR</b>	<b>FDD</b>	n1, n2, n5, n7, n8, n20, n28	n1, n2, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n2, n5, n7, n8, n20, n28	n1, n3, n7, n8, n20, n28	n1, n3, n7, n8, n20, n28
	<b>TDD</b>	n38, n40, n41, n77, n78, n75	n38, n40, n41, n77, n78, n75	n38, n40, n41, n75, n77, n78	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78
<b>4G LTE</b>	<b>FDD</b>	B1, B3, B5, B7, B8, B28, B32	B1, B3, B5, B7, B8, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B28	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32
	<b>TDD</b>	B38, B40, B41, B42	B38, B40, B41, B42	B38, B40, B41, B42, B43	B38, B40, B41, B42	B34, B38, B39, B40, B41, B42, B43	B34, B38, B39, B40, B41, B42, B43
		5G NR: 3xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 4xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA
<b>DL CA</b>							
<b>UL CA</b>		5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA	5G NR: 2x2 UL MIMO 4G LTE: 2xCA
<b>MIMO</b>		5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/ B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/ B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n5/n7/n8/n20/ n28/n38/n40/n41/n75/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B5/B7/B8/B20/ B28/B32/B38/B40/B41/B42/B43	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/ B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/ B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/ B41/B42
		5G NR: 256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM
<b>WiFi</b>	<b>802.11n 2x2</b>	-	-	-	-	-	-
	<b>802.11ac 2x2</b>	-	-	-	-	-	-
	<b>802.11ac 4x4</b>	-	-	-	-	-	-
	<b>802.11ax 2x2</b>	Yes	Yes	Yes	-	Yes	Yes
	<b>802.11ax 4x4</b>	-	-	-	Yes	-	-
	<b>Number of users</b>	up to 64	up to 64	up to 64	up to 64	up to 64	up to 64
<b>Ethernet</b>	<b>GbE LAN</b>	x2 (1GbE)	x2 (1GbE)	x2 (2.5GbE)	x2 (2.5GbE)	x2 (2.5GbE)	x2 (1GbE)
	<b>GbE WAN</b>	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)
<b>Phone</b>	<b>VoIP</b>	-	-	-	-	-	-
	<b>VoLTE</b>	-	-	-	-	-	-
<b>SIM slot</b>	<b>Micro/Mini SIM slot</b>	Micro SIM	Micro SIM	Nano SIM	Micro SIM	Micro SIM	Micro SIM
<b>Power</b>	<b>DC input</b>	DC 12 V	DC 12 V	DC 12 V	DC 12 V	DC 12 V	DC 12 V

# Frequency band comparison

## Indoor CPE

Model		Cat. 18	Cat. 12	Cat. 6	Cat. 4
		LTE5398-M904	LTE5388-M804	LTE3301-PLUS	LTE3202-M437
<b>Product name</b>		4G LTE-A Pro Indoor Router	4G LTE-A Indoor Router	4G LTE-A Indoor Router	4G LTE Indoor Router
<b>5G NR</b>	<b>FDD</b>	-	-	-	-
	<b>TDD</b>	-	-	-	-
<b>4G LTE</b>	<b>FDD</b>	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28 (28a)
	<b>TDD</b>	B38, B40, B41	B38, B40, B41	B38, B40, B41	B38, B40, B41
<b>DL CA</b>		2xCA: intra-band and inter-band	2xCA: intra-band and inter-band	B1+B1/B5/B8/B20/B28 B3+B3/B5/B7/B8/B20/B28	-
		3xCA: intra-band and inter-band	3xCA: intra-band and inter-band	B7+B5/B7/B8/B20/B28 B38+B38; B40+B40; B41+B41	-
		4xCA: intra-band and inter-band			
		5xCA: intra-band and inter-band			
		within 4 bands			
<b>UL CA</b>		2xCA: intra-band contiguous	2xCA: intra-band contiguous	-	-
		Yes	Yes	DL 2x2 MIMO	-
<b>MIMO</b>					
<b>Modulation (DL/UL)</b>		256-QAM/64-QAM	256-QAM/64-QAM	64-QAM/16-QAM	64-QAM/16-QAM
<b>WiFi</b>	<b>802.11n 2x2</b>	Yes	Yes	Yes	Yes
	<b>802.11ac 2x2</b>	-	-	Yes	Yes
	<b>802.11ac 4x4</b>	Yes	Yes	-	-
	<b>802.11ax 2x2</b>	-	-	-	-
	<b>802.11ax 4x4</b>	-	-	-	-
	<b>Number of users</b>	up to 32	up to 32	up to 32	up to 16
<b>Ethernet</b>	<b>GbE LAN</b>	x2 (1GbE)	x2 (1GbE)	x4 (1GbE)	-
	<b>GbE WAN</b>	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	-
<b>Phone</b>	<b>VoIP</b>	x1 (optional)	x1 (optional)	-	-
	<b>VoLTE</b>	x1 (optional)	x1 (optional)	-	-
<b>SIM slot</b>	<b>Micro/Mini SIM slot</b>	Micro SIM	Micro SIM	Micro SIM	Micro SIM
<b>Power</b>	<b>DC input</b>	DC 12 V	DC 12 V	DC 12 V	DC 12 V



## Corporate headquarters

**Zyxel Communications Corp.**  
Tel: +886 3 578 3942  
Fax: +886 3 578 2439  
Email: [sales@zyxel.com.tw](mailto:sales@zyxel.com.tw)  
<https://service-provider.zyxel.com>

### EMEA

**Zyxel Armenia**  
Tel: +374 96 584 694

**Zyxel Azerbaijan**  
Email: [sales.sp@zyxel.ru](mailto:sales.sp@zyxel.ru)

**Zyxel Benelux**  
Tel: +31 23 555 3689  
Fax: +31 23 557 8492

**Zyxel Bulgaria**  
Tel: +3592 4443343

**Zyxel Czech Republic**  
Tel: +420 241 091 350  
Hotline: +420 241 774 665  
Fax: +420 241 091 359

**Zyxel Denmark**  
Tel: +45 39 55 07 00  
Fax: +45 39 55 07 07

**Zyxel Egypt**  
Email: [da.sales@zyxel.com.tw](mailto:da.sales@zyxel.com.tw)

**Zyxel Finland**  
Tel: +358 9 4780 8400

**Zyxel France**  
Tel: +33 (0) 4 72 52 97 97  
Fax: +33 (0) 4 72 52 19 20

**Zyxel Germany**  
Tel: +49 (0) 2405 6909 0  
Fax: +49 (0) 2405 6909 99

**Zyxel Hungary & SEE**  
Tel: +36 1 848 0690

**Zyxel Iberia**  
Tel: +34 911 792 100

**Zyxel Israel**  
Email: [da.sales@zyxel.com.tw](mailto:da.sales@zyxel.com.tw)

**Zyxel Italy**  
Tel: +39 011 2308000

**Zyxel Kazakhstan**  
Tel: +7 727 350 5683  
Fax: +7 727 2590 689

**Zyxel Norway**  
Tel: +47 22 80 61 80  
Fax: +47 22 80 61 81

**Zyxel Poland**  
Tel: +48 223 338 250  
Hotline: +48 226 521 626  
Fax: +48 223 338 251

**Zyxel Romania**  
Tel: +40 31 0809 888  
Fax: +40 31 0809 890

**Zyxel Slovakia**  
Tel: +421 220 861 847  
Hotline: +421 220 861 848  
Fax: +421 243 193 990

**Zyxel Sweden**  
Tel: +46 8 55 77 60 60  
Fax: +46 8 55 77 60 61  
Email: [isp@zyxel.eu](mailto:isp@zyxel.eu)

**Zyxel Spain**  
Tel: +34 911 792 100

**Zyxel Turkey**  
Tel: +90 212 314 18 00  
Fax: +90 212 220 25 26

**Zyxel UK**  
Tel: +44 (0) 118 9121 700  
Fax: +44 (0) 118 9797 277

**Zyxel Ukraine**  
Tel: +380 89 323 9959

### APAC

**Zyxel Australia**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

**Zyxel India**  
Tel: +91 11 4760 8800  
Fax: +91 11 4052 3393  
Email: [info@zyxel.in](mailto:info@zyxel.in)

**Zyxel Japan**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

**Zyxel Malaysia**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

**Zyxel Philippine**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

**Zyxel Singapore**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

**Zyxel Taiwan (Taipei)**  
Tel: +886 2 2739 9889  
Fax: +886 2 8913 1896  
Email: [sales\\_tw@zyxel.com.tw](mailto:sales_tw@zyxel.com.tw)

**Zyxel Thailand**  
Tel: +66 (0) 2831 5315  
Fax: +66 (0) 2831 5395  
Email: [info@zyxel.co.th](mailto:info@zyxel.co.th)

**Zyxel Vietnam**  
Email: [apac.sales@zyxel.com.tw](mailto:apac.sales@zyxel.com.tw)

### North America

**Zyxel USA**  
Tel: +1 714 632 0882  
+1 800 255 4101 (free)  
Fax: +1 714 632 0858  
Email: [keyaccount@zyxel.com](mailto:keyaccount@zyxel.com)

**Zyxel Canada**  
Tel: +1 714 632 0882  
+1 800 255 4101 (free)  
Fax: +1 714 632 0858  
Email: [keyaccount@zyxel.com](mailto:keyaccount@zyxel.com)

### South America

**Zyxel Argentina**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Brazil**  
Tel: +55 (11) 3373 7470  
Fax: +55 (11) 3373 7510  
Email: [comercial@zyxel.com.br](mailto:comercial@zyxel.com.br)

**Zyxel Bolivia**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Chile**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Colombia**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Ecuador**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Paraguay**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Peru**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

**Zyxel Uruguay**  
Email: [sa.sales@zyxel.com.tw](mailto:sa.sales@zyxel.com.tw)

For more product information, visit us on the web at  
<https://service-provider.zyxel.com>

Copyright © 2023 Zyxel and/or its affiliates. All rights reserved.  
All specifications are subject to change without notice.

